

Experion Series-C I/O Specification



EP03-490-520

Release 520

Dec 2021, Version 1.5

CC-PAOH01 CC-PAOX01		Analog Output 16pt HART Analog Output 16pt w/o HART	16		√
	CC-TAOX01	AO IOTA		6	
	CC-TAOX11	AO IOTA Red.		12	√
CC-PAOH51		Analog Output 16pt HART	16		√
	CC-TAOX51	AO IOTA		6	
	CC-TAOX61	AO IOTA Red		12	√
CC-PAON01		Analog Output 16pt w/o HART	16		√
	CC-TAON01	AO IOTA		6	
	CC-TAON11	AO IOTA Red		12	√
CC-PDIL01 CC-PDIS01		Digital Input 24V Digital Input Sequence of Events	32		√
	CC-TDIL01	DI 24V IOTA		9	
	CC-TDIL11	DI 24V IOTA Red.		12	√
CC-PDIL51		Digital Input 24V	32		√
	CC-TDIL51	DI 24V IOTA		9	
	CC-TDIL61	DI 24V IOTA Red.		12	√
CC-PDIH01		Digital Input High Voltage	32		√
	CC-TDI110	DI 110V IOTA		9	
	CC-TDI120	DI 110V IOTA Red.		12	√
	CC-TDI220	DI 220VAC IOTA		9	
	CC-TDI230	DI 220VAC IOTA Red.		12	√
CC-PDOB01		DO - 24V Bussed Out	32		√
	CC-TDOB01	DO 24V Buss IOTA		9	
	CC-TDOB11	DO 24V Buss IOTA Red.		12	√
	CC-TDOR01	DO Relay IOTA		6	
	CC-TDOR11	DO Relay IOTA Red.		12	√
	CC-SDOR01	DO Relay Extension Board		12	
CC-PUIO01		Universal Input Output	32		√
	CC-TUIO01	Universal Input Output IOTA		12	
	CC-TUIO11	Universal Input Output IOTA Red.		18	√
CC-PUIO31		Universal Input Output	32		√

5.12. Digital Input 24VDC – CC-PDIL01

Function

The Digital Input 24VDC accepts 24VDC signals as discrete inputs.

Notable Features

- Extensive internal diagnostics for data integrity
- Open wire detection
- Optional redundancy
- Internal or external field power selection
- On board excitation power (no need for marshalling power)
- Supplies Non-incendive field power
- Direct / Reverse Input Indication
- Galvanic isolation

Open-wire Bad PV Detection

This Series C IO function will be able to detect and annunciate Open field wire. In addition, a seemingly-valid PV from a channel diagnosed as having a Open-wire will provide a status of “invalid” (thus preventing incorrect control action).

Detail Specifications - DI 24VDC

Parameter	Specification		
Input / Output Model	CC-PDIL01 - 24Volt Digital Input		
IOTA Models	CC-TDIL01	Non Redundant	9"
	CC-TDIL11	Redundant	12"
	CC-GDIL11	Redundant	12"
	CC-GDIL21	Non Redundant	6"
	CC-GDIL01	Redundant for exp.	12"
	CC-SDXX01	GI-IS I/O Expander	12"
Input Channels	32		
Galvanic Isolation (any input terminal voltage referenced to common)	1500 VAC RMS or ±1500 VDC		
Isolation Technique	Optical (in IOM)		
DI Power Voltage Range	18 to 30 VDC		
ON Sense Voltage/Current	13 VDC (min) or 3 mA (min)		
OFF Sense Voltage/Current	5 VDC (max) or 1.2 mA (max)		
Input Impedance	4.2 KΩ		
Absolute Delay Across Input Filter and Isolation	5 ms ± 20%		
Field Resistance for Guaranteed ON Condition	300 Ωmax @ 15 VDC		
Field Resistance for Guaranteed OFF Condition	30 KΩmin @ 30 VDC		

DI Function Matrix

			Function						
IOM	NR IOTA	Red IOTA	24V	HV	SOE	Fast Scan	Open Wire	Isolation	IS
CC-PDIL01	CC-TDIL01	CC-TDIL11	◆			◆	◆	1500V	
CC-PDIL51	CC-TDIL51	CC-TDIL61	◆			◆		1000V	
CC-PDIS01	CC-TDIL01	CC-TDIL11	◆		◆	◆	◆	1500V	
CC-PDIL01	CC-GDIL21	CC-GDIL11	◆			◆	◆	Inf.	◆
CC-PDIH01	CC-TDI110	CC-TDI120		110V			◆	1500V	
CC-PDIH01	CC-TDI220	CC-TDI230		220V			◆	1500V	
CC-PUIO31	CC-TUIO31	CC-TUIO41	◆		◆	◆	◆	None	

DO Function Matrix

				Function					
IOM	NR IOTA	Red IOTA	Support IOTA	Open Wire Det	Short Prot.	Output Type	Out. I	Isolation	IS
CC-PDOB01	CC-TDOB01	CC-TDOB11		◆	◆	Source	0.5A	1500V	
CC-PDOB01	CC-TDOR01	CC-TDOR11	CC-SDOR01	◆		Dry Contact	3A	Inf.	
CC-PDOB01	----	CC-GDOL11	CC-SDXX01	◆	◆	Source	48ma	Inf.	◆
CC-PDOD51	CC-TDOD51	CC-TDOD61		◆	◆	Sink	0.1A	1000V	
CC-PUIO31	CC-TUIO31	CC-TUIO41	◆	◆	◆	Source	0.5A	None	