

Experion Series-C I/O Specification



**EP03-490-520**

**Release 520**

**Dec 2021, Version 1.5**

	CC-TUIO31	Universal Input Output IOTA		9	
	CC-TUIO41	Universal Input Output IOTA Red.		12	√

## 5. Specifications

Specifications for Series-C I/O modules are shown below.

For information on environmental specifications, please refer to the Series-C Platform Specification and Technical data sheet EP03-520-xxx.

### 5.1. Analog Input with HART – CC-PAIH01 / 02

#### Function

The Analog Input Module accepts high level current or voltage inputs from transmitters and sensing devices.

#### Notable Features

- Extensive self-diagnostics
- Optional redundancy
- Open Wire Detection
- Supplies non-incendive field power
- Non-incendive Power
- HART-capable, multivariable instruments and multiple modems for fast collection of control variables
- Fast loop scan
- PV protection through an open wire detection diagnostic
- Open-wire Bad PV Detection

#### Detail Specifications - Analog Input with HART

Parameter	Specification	
Input / Output Model	CC-PAIH02 - High-Level Analog Input with HART	
IOTA Models	Non-Redundant	Redundant
	CC-TAIX01	CC-TAIX11
	CC-GAIX21	CC-GAIX11
	CC-TAID01	CC-TAID11
Input Type	Voltage, current (2-wire or self-powered transmitters)	
Input Channels <sup>1</sup>	16 Channels (12 Single Ended / 4 Differential )	
Common Mode Rejection Ratio, dc to 60 Hz (500 $\Omega$ source imbalance)	70 dB	
Common Mode Voltage, dc to 60 Hz	-6 to +5 V peak	
A/D Converter Resolution	16 bits	
Input Range <sup>1</sup>	0 to 5 V, 1 to 5 V, 0.4 to 2 V, 4-20 mA (through 250 $\Omega$ )	
Normal Mode Rejection Ratio, at 60 Hz	19 dB	

Parameter	Specification
Normal Mode Filter Response	Single-pole RC, -3 dB @ 6.5 Hz
Maximum Normal Mode Input (differential inputs, no damage)	± 30 Volts
Crosstalk, dc to 60 Hz (channel-to-channel)	-60 dB
Input Impedance (voltage inputs)	> 10 M Ω powered
Input Scan Rate	50 ms
Hardware Accuracy (@ CMV = 0 V)	± 0.075% of full-scale (23.5°± 2°C) ± 0.15% of full-scale (0 to 60°C)
Transmitter Field Power Conditioning	Individually Protected Current Limiting Circuits for Class 1, Div 2 non-incendive interfacing. No fusing required
<p>Note 1: CC-PAIH01 supports voltage inputs for channels 13-16 CC-PAIH02 supports voltage inputs for channels 1-16 when used with CC-TAIDx1 IOTA. Each channel's 250-Ohm load resistor is connected to the input terminal through a wire jumper on the IOTA. This jumper should be cut by the user on channels to be used with voltage transmitters. For channels 13-16 the low-side input connection is normally connected to system common by a wire jumper on the IOTA. This jumper may be cut by the user to enable differential operation subject to operating within the CMV specification.</p>	