

PanelView Plus to PanelView Plus 6 Catalog Number Conversions

Topic	Page
About This Publication	1
Platform Comparisons	2
Windows CE 6.0 Operating System	3
PanelView Plus 6 - 400 and 600 Terminal Selections	4
Catalog Number Conversion Tables - 400 and 600 Terminals	5
Legacy PanelView Plus 400 and 600 Terminal Support	7
PanelView Plus 6 - 700 to 1500 Product Selections	9
PanelView Plus 6 - 700 to 1500 Accessories	10
Catalog Number Conversion Tables - 700 to 1500 Terminals	12
Logic Module Conversions - 700 to 1500 Terminals	24
Legacy PanelView Plus 700 to 1500 Terminal Support	25
Additional Resources	27

About This Publication

This publication provides information about converting the following terminals to the new generation PanelView™ Plus 6 terminals:

- PanelView Plus and PanelView Plus CE 700 to 1500 terminals
- PanelView Plus 400 and 600 terminals
- PanelView Plus Compact terminals

The new PanelView Plus 6 platform is available with or without extended features and file viewers. There is no longer a distinction between PanelView Plus and PanelView Plus CE terminals.

PanelView Plus 6 -700 to 1500 Product Selections

The table shows the catalog number breakdown for the PanelView Plus 6 - 700 to 1500 terminals.

Bulletin Number	Input Type	Display Size	Display Type	Communication	Power	Operating System	Special Option
2711P-	K = Keypad T = Touch	4 = 3.5 in. 6 = 5.7in.	C = Color M - Grayscale	4 = Ethernet, RS-232, (2) USB Host, (1) USB Device 20 = RS-232, (1) USB Host, (1) USB Device	A = AC D = DC	8 = Windows CE 6.0 operating system 9 = Windows CE 6.0 operating system with extended features and viewers	K = Conformal-coated

[Table 11](#) and [Table 12](#) list the catalog numbers available for the PanelView Plus 6 terminals. These catalog numbers are referenced in the [Catalog Number Conversion Tables - 700 to 1500 Terminals](#) starting on page [12](#).

Table 11 - PanelView Plus 6 Terminals without Extended Features

Cat. No.			Display		Communication		Input Power	Memory RAM/Nonvolatile Storage
Keypad	Touch	Keypad/Touch	Size	Type	RS-232	Ethernet		
700 Model								
2711P-K7C4D8	2711P-T7C4D8	2711P-B7C4D8	6.5-in.	Color	•	•	DC	512 MB/512 MB
-	2711P-T7C4D8K	-			•	•	DC	512 MB/512 MB
2711P-K7C4A8	2711P-T7C4A8	2711P-B7C4A8			•	•	AC	512 MB/512 MB
1000 Model								
2711P-K10C4D8	2711P-T10C4D8	2711P-B10C4D8	10.4-in	Color	•	•	DC	512 MB/512 MB
2711P-K10C4A8	2711P-T10C4A8	2711P-B10C4A8			•	•	AC	512 MB/512 MB
1250 Model								
2711P-K12C4D8	2711P-T12C4D8	2711P-B12C4D8	12.1-in	Color	•	•	DC	512 MB/512 MB
-	2711P-T12C4D8K	-			•	•	DC	512 MB/512 MB
2711P-K12C4A8	2711P-T12C4A8	2711P-B12C4A8			•	•	AC	512 MB/512 MB
1500 Model								
2711P-K15C4D8	2711P-T15C4D8	2711P-B15C4D8	15-in.	Color	•	•	DC	512 MB/512 MB
2711P-K15C4A8	2711P-T15C4A8	2711P-B15C4A8			•	•	AC	512 MB/512 MB

Table 12 - PanelView Plus 6 Terminals with Extended Features

Cat. No.			Display		Communication		Input Power	Memory RAM/Nonvolatile Storage
Keypad	Touch	Keypad/Touch	Size	Type	RS-232	Ethernet		
700 Model								
2711P-K7C4D9	2711P-T7C4D9	2711P-B7C4D9	6.5-in.	Color	•	•	DC	512 MB/512 MB
2711P-K7C4A9	2711P-T7C4A9	2711P-B7C4A9			•	•	AC	512 MB/512 MB
1000 Model								
2711P-K10C4D9	2711P-T10C4D9	2711P-B10C4D9	10.4-in	Color	•	•	DC	512 MB/512 MB
2711P-K10C4A9	2711P-T10C4A9	2711P-B10C4A9			•	•	AC	512 MB/512 MB
1250 Model								
2711P-K12C4D9	2711P-T12C4D9	2711P-B12C4D9	12.1-in	Color	•	•	DC	512 MB/512 MB
2711P-K12C4A9	2711P-T12C4A9	2711P-B12C4A9			•	•	AC	512 MB/512 MB
1500 Model								
2711P-K15C4D9	2711P-T15C4D9	2711P-B15C4D9	15-in.	Color	•	•	DC	512 MB/512 MB
2711P-K15C4A9	2711P-T15C4A9	2711P-B15C4A9			•	•	AC	512 MB/512 MB

Table 21 - Catalog Number Conversions for 1000 Keypad Terminals

From Existing PanelView Plus/PanelView Plus CE	To New PanelView Plus 6	+	Communication Module ⁽¹⁾	
1000 Keypad Terminals				
Configured terminal with ControlNet communication	2711P-K10C15A1	2711P-K10C4A8	+	2711P-RN15S
	2711P-K10C15A2			
	2711P-K10C15A6	2711P-K10C4A9	+	2711P-RN15S
	2711P-K10C15A7			
	2711P-K10C15B1	2711P-K10C4A8	+	2711P-RN15S
	2711P-K10C15B2			
	2711P-K10C15D1	2711P-K10C4D8	+	2711P-RN15S
	2711P-K10C15D2			
	2711P-K10C15D6	2711P-K10C4D9	+	2711P-RN15S
2711P-K10C15D7				
Base unit terminal with built-in Ethernet and RS-232 communication ports	2711P-K10C4A1	2711P-K10C4A8	+	2711P-RN20 provides additional Ethernet port
	2711P-K10C4A2			
	2711P-K10C4A6	2711P-K10C4A9	+	2711P-RN20 provides additional Ethernet port
	2711P-K10C4A7			
	2711P-K10C4B1	2711P-K10C4A8	+	2711P-RN20 provides additional Ethernet port
	2711P-K10C4B2			
	2711P-K10C4D1	2711P-K10C4D8	+	2711P-RN20 provides additional Ethernet port
	2711P-K10C4D2			
	2711P-K10C4D6	2711P-K10C4D9	+	2711P-RN20 provides additional Ethernet port
2711P-K10C4D7				
Configured terminal with DH+ /DH-485 communication	2711P-K10C6A1	2711P-K10C4A8	+	2711P-RN6
	2711P-K10C6A2			
	2711P-K10C6A6	2711P-K10C4A9	+	2711P-RN6
	2711P-K10C6A7			
	2711P-K10C6B1	2711P-K10C4A8	+	2711P-RN6
	2711P-K10C6B2			
	2711P-K10C6D1	2711P-K10C4D8	+	2711P-RN6
	2711P-K10C6D2			
	2711P-K10C6D6	2711P-K10C4D9	+	2711P-RN6
2711P-K10C6D7				

(1) Refer to [Legacy PanelView Plus 700 to 1500 Terminal Support on page 25](#) if your application requires remote I/O or DeviceNet communication.